
Voice Mail

This feature offers the advantage of an answering machine without the hassle of another piece of equipment for recording or playback. This feature must be accompanied with call-forwarding features.

\$12.00 Installation Fee

\$4.50 monthly

Includes

- Call Forward All
- Call Forward Busy Line
- Call Forward Don't answer

A distinctive dial tone indicates there is a message in the voicemail box.

Call Forward All

When activated ALL calls go directly to voicemail, you may hear a ring, but you will not be able to answer:

To activate:

- Pick up the handset
- Dial *72
- You will hear 3 beeps
- Dial 520-383-5656, 520-361-2121, or 520-362-2121 (depending on the exchange)
- You will hear 3 beeps
- hang up.

To deactivate:

- Pick up handset
- Dial *73
- You will hear 3 beeps
- Hang up

Call Forward Busy Line

When your line is in use instead of hearing a busy signal, your callers will be transferred to voicemail.

To activate:

- Pick up handset
- Dial *90
- You will hear 3 beeps
- Dial 520-383-5656, 520-361-2121, or 520-362-2121 (depending on your exchange)
- You will hear 3 beeps
- Hang up

To deactivate:

- Pick up handset
- Dial *91
- You will hear 3 beeps
- Hang up

Call Forward Don't Answer

After a predetermined number of rings, your calls will be transferred to voicemail.

To activate:

- Pick up handset
- Dial *92
- You will hear 3 beeps
- Dial 520-383-5656, 520-361-2121, or 520-362-2121 (depending on exchange)
- You will hear 3 beeps
- Hang up

To deactivate:

- Pick up handset
- Dial *93
- You will hear 3 beeps
- Hang up

*99 Master Deactivation - This will deactivate any and all forwarding features. Note: CFDA & CFBL can be activated at the same time. However, CFA takes precedence over the other two.